

PORODO



Porodo

**LARA 30000mAh Power Bank
with Integrated Cables & Flashlight**

SKU: PDPBJ261BK

Table of Contents

Product Overview	2
Specifications	2
Product Design	3
Key Features	4
Usage Instructions	4
Digital Display	5
Safety Precautions	5
Disposal	6
Warranty	7
Contact Us	7

Product Overview

The Porodo LARA 30000mAh Power Bank is a high-capacity, multifunctional charging solution designed to keep your devices powered up on the go. With its impressive 30,000mAh capacity, it offers extended usage, making it perfect for travel, outdoor adventures, or everyday use. The power bank features integrated cables for easy charging and a built-in flashlight for added convenience. Its portable handle ensures easy carrying, while the PD 20W fast charging capability allows for quick power-ups. The LARA power bank is universally compatible with a wide range of devices, from smartphones to tablets, and includes built-in safety features to protect against overcharging and overheating. Whether you're on the move or simply need a reliable backup, the Porodo LARA Power Bank offers a practical and safe solution to keep your devices charged.

Specifications

Battery Capacity	30000mAh
USB-C1 Input	5V/2.1A
USB-C2 Input	5V/3A, 9V/2.22A, 12V/1.67A
USB Line Input	5V/2.1A
USB-C2 Output	5V/3A, 9V/2.22A, 12V/1.67A
USB-A1 Output	5V/2.1A
USB-A2 Output	5V/3A, 9V/2,22A, 10V/2,25A, 12V/1,67A
Micro Line Output	5V/2A
Lightning Line Output	5V/2A
Type-C Line Output	5V/2.1A

Sharing Output	5V/3A, 15W Max
Product Weight	730g
Product Size	49 x 69 x 146mm
Model Number	PDPBJ261

Product Design



1. LED Lamp
2. Cable Detachment
3. Ergonomic ABS Handle
4. Micro USB cable
Type-C cable
Lightning cable
USB Input cable
5. Digital Display
6. Switch
7. Type-C Port
8. USB 2
9. Type-C Port
10. USB 1

Key Features

1. Integrated Cables & Flashlight: Convenient integrated cables make charging easier, while the built-in flashlight provides an additional layer of functionality.
2. Portable Handle: The power bank features a portable handle for easy carrying, making it perfect for travel and outdoor use.
3. Fast Charging (PD 20W): Equipped with PD 20W fast charging, the LARA power bank delivers rapid charging to your devices, saving you time.
4. Universal Compatibility: Compatible with a wide range of devices, from smartphones to tablets and other USB-powered electronics.
5. Built-in Safety Feature: Designed with built-in safety features to protect against overcharging and overheating, ensuring your devices stay safe while charging.

Digital Display

1. Battery Check: To check the remaining battery level, press the power button once. The power display will show the current battery status.
2. Turn Off Power Display: To turn off the power display, press the power button again. This will deactivate the display to save energy when not in use.

Usage Instructions

- 1. Light Control:** Press and hold the button to turn the flashlight on or off. This allows easy access to a light source when needed.
- 2. Mobile Power Charging:** The device can be charged through the built-in USB cable, or it can be charged using the user's own Type-C cable (with a maximum PD20W output). When charging, the battery display will show the charging progress. The indicator will display 100% once fully charged. Please disconnect the charger after the battery reaches full capacity to preserve the battery life.
- 3. Charging Mobile Devices:** You can use the device to charge your mobile device using the built-in Micro USB, Lightning, or Type-C cable (with a maximum output of PD20W). Additionally, you can connect the device to a USB-A to USB-C cable for charging at a 22.5W rate (via the USB-A1/A2 ports). Please note that some device brands may require alternative cables for proper charging. When charging multiple devices simultaneously, the maximum charging speed is limited to 5V/3A.

Safety Precautions

- 1.** If the power bank becomes uncomfortably hot or reaches excessive temperatures during use or while charging, it is critical to disconnect it from both the power supply and any mobile devices without delay. This is important to prevent potential damage to the power bank, connected devices, or even to ensure user safety. Allow the power bank to cool down naturally in a well-ventilated area before reconnecting or resuming use.
- 2.** Do not use or charge the power bank in excessively hot or humid environments.
- 3.** Always use the correct cable for charging your devices. Using incompatible cables may cause overheating or damage.
- 4.** Ensure the charging port is clean and free from debris before connecting any cables.

- 5.** Do not expose the power bank to water, rain, or other liquids. It is not water-resistant and may malfunction or become damaged when wet.
- 6.** Store the power bank in a cool, dry place when not in use. Avoid direct sunlight and high-temperature areas such as next to radiators or in cars.
- 7.** Keep the power bank away from flammable materials to prevent any risk of fire.
- 8.** Do not attempt to open, disassemble, or repair the power bank yourself. Contact authorized service centers for any repairs or issues. Unauthorized disassembly may void the warranty and cause safety hazards, such as electrical shocks or battery leakage.
- 9.** Do not use the power bank if the cable or the power bank itself is damaged. A short-circuit or overload can occur if the power bank is not functioning properly.
- 10.** If the power bank is excessively hot or showing signs of swelling, stop using it immediately and dispose of it responsibly.
- 11.** Handle the power bank gently to avoid accidental drops or impacts. Physical damage can affect the performance or safety of the battery.
- 12.** Keep Away from Children: Keep the power bank out of reach of children to avoid accidental ingestion or injury from misuse.

Disposal

This product must not be disposed of as unsorted household waste. It is important to separate such waste for proper treatment and recycling, in compliance with local waste management regulations.

Warranty

Products that you buy directly from our **Porodo** website or shop come with a 24-month warranty.

When you buy **Porodo** products from any of our approved sellers, you only get a 12-month warranty. If you want to extend this warranty, go to our website at **porodo.net/warranty** and fill out the form with your information. Don't forget to upload a picture of the product too. After we've checked and accepted your request, we'll send you an email to confirm that your product's warranty has been extended.

For more info, please check:
porodo.net/warranty

Contact Us

If you have any questions about this Privacy Policy, please contact us at:
info@porodo.net

Website: **porodo.net**

Service Support: **support@porodo.net**

Instagram: **porodo**