

PORODO



Porodo

Zebro Smart Watch with 1.43" Display

SKU: PD-ZEBRO

Table of Contents

Overview	2
Specifications	2
App Connectivity	3
Bluetooth Connection Verification	4
Notification Settings	4
Function Introduction	4
Additional Settings	7
Warranty	9
Contact Us	9

Overview

Thank you for purchasing our product. By reading this manual, you will gain a comprehensive understanding of the device's operation. The smartwatch connects to your smartphone via Bluetooth, offering a variety of practical functions to enhance mobile phone usage. The smart watch provides different features to monitor the user's activity and health. Please note that the Company reserves the right to alter the contents of this manual at any time without prior notification. This product is NOT intended to serve as a medical device. Health-related data and recommendations provided are solely for informational purposes, and should not be construed as medical advice or used for diagnosis or treatment.

Specifications

Watch Case	Zinc Alloy
Screen Size	1.43"
Screen Resolution	AMOLED 466×466
Flash Memory	128MB
Charging Time	2-3H
Working Time	2 to 3 Days (Bluetooth), 5 to 7 Days (without Bluetooth)
Battery Capacity	260mAh Lithium Polymer
G-Sensor	SC7A20E
IC Sensor	Tianyi Hexin 3605
Bluetooth	V3.0, V5.0
Water Resistant Level	IP65
System Compatibility	Android 5.0 and above, iOS 9.0 and above.

App Connectivity

Download and install the "FereFit" app on your phone to connect with the watch.

1. For iOS or Android users, scan the provided QR code using your phone's browser to open the interface and proceed with the setup.

A QR code is provided below for direct access to the "FereFit" app download.



Android/iOS

2. Alternatively, search for "FereFit" in the App Store or the Google Play. Download and install the app.

Note: You will encounter several permission requests throughout the installation phase. It is imperative that you select "Agree" for each prompt to proceed. The watch must be connected via two Bluetooth connections, versions 3.0 and 5.0, to access all features.

3. Bluetooth 5.0 Connection

After installing the "FereFit" app, activate your phone's Bluetooth. The "FereFit" app will prompt you to enable necessary notifications. To pair, go to the bottom right corner of the app, select the scanning option, look for the device name "Zebro" and connect. Some Android devices may require GPS activation to pair.

4. Bluetooth 3.0 Connection

1. Activate the watch's Bluetooth 3.0.

2. Enable Bluetooth on your phone and select "Zebro" from the list of devices. Follow on-screen prompts to establish the connection.

Bluetooth Connection Verification

A successful connection is indicated by the status bar displaying the Bluetooth icon in blue for both 3.0 and 5.0 connections. If the icon turns gray, the Bluetooth link has been lost.

Notification Settings

Due to the variance in Bluetooth protocols across different phone brands, the connection may occasionally become unstable. If issues arise, you can toggle the phone's Bluetooth off and on, or reset the watch to its factory settings to resolve the problem.

A. Setting Up Notification

To enable notifications for incoming mail on your smartwatch, navigate to 'Settings' > 'Application Management'. Search for "FereFit" and select 'Permissions Management'. Ensure all permissions are enabled for "FereFit".

Note: To prevent the watch from being affected by power-saving features, especially when the phone's battery is low, add "FereFit" to the list within the power-saving settings.

B. Troubleshooting

Should you fail to receive a notification, it is important to note that the watch's notification function is an extension of your mobile's notification features, such as calls. If your mobile does not receive a notification, the watch will similarly not receive it. To activate the notification feature, configure the settings within the "FereFit" app to allow the notifications to be displayed.

Function Introduction

Encoder: Rotate the dial on the watch's standby screen to switch between watch faces or scroll through menu options. The full-star style menu allows for zooming and maximizing applications directly from this interface for enhanced usability.

Split Screen: Swipe right on the watch face screen to access split-screen mode, allowing you to view and select different functions simultaneously.

Dial Pushing: Choose from analog pointers, digital displays, or custom designs.

Phone: Place calls directly from your watch. View recent call logs and contacts. Manage incoming calls with options for vibration or sound notifications.

Contacts: Sync up to 10 contacts from your smartphone to your watch through the app.

Call Records: Keep your call logs in sync between your watch and smartphone.

Dialing Keypad: Make phone calls directly from your watch using the built-in keypad.

Activity Data: Monitor daily steps, activity history, calories burned, and distance traveled. The data resets automatically at midnight each day.

Dial Pushing: Choose from analog pointers, digital displays, or custom designs.

Phone: Place calls directly from your watch. View recent call logs and contacts. Manage incoming calls with options for vibration or sound notifications.

Contacts: Sync up to 10 contacts from your smartphone to your watch through the app.

Call Records: Keep your call logs in sync between your watch and smartphone.

Dialing Keypad: Make phone calls directly from your watch using the built-in keypad.

Activity Data: Monitor daily steps, activity history, calories burned, and distance traveled. The data resets automatically at midnight each day.
Dial Pushing: Choose from analog pointers, digital displays, or custom designs.

Phone: Place calls directly from your watch. View recent call logs and contacts. Manage incoming calls with options for vibration or sound notifications.

Contacts: Sync up to 10 contacts from your smartphone to your watch through the app.

Call Records: Keep your call logs in sync between your watch and smartphone.

Dialing Keypad: Make phone calls directly from your watch using the built-in keypad.

Activity Data: Monitor daily steps, activity history, calories burned, and distance traveled. The data resets automatically at midnight each day.
Dial Pushing: Choose from analog pointers, digital displays, or custom designs.

Phone: Place calls directly from your watch. View recent call logs and contacts. Manage incoming calls with options for vibration or sound notifications.

Contacts: Sync up to 10 contacts from your smartphone to your watch through the app.

Call Records: Keep your call logs in sync between your watch and smartphone.

Dialing Keypad: Make phone calls directly from your watch using the built-in keypad.

Activity Data: Monitor daily steps, activity history, calories burned, and distance traveled. The data resets automatically at midnight each day.

Alarm Clock: Sync up to three alarms through the app or set them directly on the watch.

Voice Assistant: Use Siri by tapping the voice assistant icon on the watch after connecting via Bluetooth 3.0 or 5.0.

Sleep Monitoring: Tracks sleep duration and quality from 9 PM to 9 AM, aiding in adjusting rest periods and improving sleep quality. Access sleep data synchronously through the app.

Fitness Tracking: The watch features various sports modes including running, walking, soccer, badminton, tennis, basketball, table tennis, and cycling.

Remote Photo Capture: Control your phone's camera via Bluetooth. Ensure your phone's screen is unlocked, access the camera through the watch, and take photos that save directly to your phone's album.

Find My Phone: Activate your phone's ringtone via the watch by connecting through Bluetooth, useful for locating your device. The ringing continues until canceled by user.

Device Search: From the app, initiate a search that causes the watch to vibrate continuously until the process is canceled or the device is found.

Weather: Check the weather forecast for the next 7 days directly on your watch after connecting to Bluetooth.

Stopwatch: Utilize the stopwatch for single or multiple timing sessions.

Breathing: Set exercise and breathing intervals to manage your breathing exercises effectively.

Calculator: Use the built-in calculator for quick arithmetic operations.

Menu Style: Customize the menu interface according to your personal preferences.

Settings: Access system settings to configure various aspects of your watch.

Component Functions: Swipe right on the dial interface to quickly access functions like heart rate monitoring, sleep tracking, weather updates, music control, and location services.

Female Health Function: Monitor menstrual cycles and ovulation to stay informed about fertility windows.

Games: Enjoy preloaded games such as "Dumb Birds Fly First."

Location Information: Display your current location by connecting the watch to your smartphone via Bluetooth 5.0 and enabling location permissions.

Customizable Settings: Personalize various watch settings to suit your needs.

Additional Settings

Screen On: Adjust how long the display remains active.

Screen Duration: Set the screen's active time to conserve battery or keep it readily available.

Raise to Wake: Enable or disable the raise-to-wake function to turn the screen on or off by raising your wrist.

Brightness Adjustment: Adjust the screen brightness to suit different lighting conditions.

Do Not Disturb Mode: Activate this mode to prevent any alerts or notifications from disturbing you.

Drainage Function: Shake your hand to enhance the drainage effect, improving device cleanliness.

Password Setting: Secure your device by setting a personal password. Use '8888' as the default unlock code.

Connect to Your Phone: Easily sync your watch by scanning the QR code and downloading the FereFit APP on your mobile device.

Power Saving Mode: Optimize battery life by dimming the screen brightness and disabling vibration.

Language Switching: Choose from multiple language options to suit your preference.

Time Setting: Sync the time with your app or manually adjust it on your watch.

Date Setting: Keep the date updated by synchronizing with your app or setting it manually.

Restore Factory Settings: Reset your device to factory settings to resolve any software issues.

Shutdown: Power off your watch through the settings menu.

About: Access detailed information about your watch, including model, software version, and MAC address.

Warranty

Products that you buy directly from our **Porodo** website or shop come with a 24-month warranty.

When you buy **Porodo** products from any of our approved sellers, you only get a 12-month warranty. If you want to extend this warranty, go to our website at **porodo.net/warranty** and fill out the form with your information. Don't forget to upload a picture of the product too. After we've checked and accepted your request, we'll send you an email to confirm that your product's warranty has been extended.

For more info, please check:
porodo.net/warranty

Contact Us

If you have any questions about this Privacy Policy, please contact us at:
info@porodo.net

Website: **porodo.net**

Service Support: **support@porodo.net**

Instagram: **porodo**