

USER MANUAL



MULTI-PORT SUPER HUB 4 USB-C / 2 USB-A

PD-FWCH009



Overview:

PD-FWCH009 universal hole timing socket power supply beautiful appearance, PC flame retardant plastic shell, internal structure rigorous, superior performance. This product is equipped with timing charging function and safety door, 1-24 hours timing function is mainly used at night or unattended, set the charging time, can well prevent the charging time is too long caused by the equipment current overload, the end of the timing time, equipment from the plug power off, so as to ensure the safety of electrical appliances. The safety door prevents direct finger contact with the metal in the jack to prevent electric shock. PD-FWCH009 universal hole timing socket, widely used in all kinds of electrical equipment plug, with switching power control, timing button control, safety door, features: timing, shell fire retardant, low energy consumption, residual pressure and so on.

Parameter:

Rated Current:10 A(MAX)
Rated Power:3000W
Output Port:6 x socket Combo 6 x USB
USB C output:36W 5V/3A,12V/3A,15V/2.4A,20V/1.8A USB A QC3.0 output:24W
5V/3A,9V/2.6A,12V/2A Total Output:60w
Rated Voltage:100v-250v
Material:PC fire retardant

Installation instructions

1. The power use method of PD-FWCH009 universal hole timing socket is the same as that of general socket. Before use, please loosen the power cord to avoid the danger of heat accumulation caused by the winding of the wire; If necessary, open the timing button and set the charging duration from 1 to 24 hours.

2. In order to ensure the normal use of the socket, ensure that the power supply voltage does not exceed 250V and the plug grounding equipment is correctly connected before use.

For more information, please contact our support team:

support@porodo.net



Made in China

www.porodo.net

[/porodo](https://www.instagram.com/porodo)

[/myporodo](https://www.facebook.com/myporodo)